

SP8647

250MHz÷10/11

The SP8647 is an ECL variable modulus divider, with ECL10K and TTL/CMOS compatible outputs. It divides by 10 when either of the ECL control inputs, <u>PE1</u> or <u>PE2</u>, is in the high state and by 11 when both are low (or open circuit).

The two clock inputs are interchangeable and either will act as a clock inhibit when connected to an ECL high level. Normally, one input is left open circuit and the other is AC-coupled, with externally applied bias.

FEATURES

- ECL Compatible Inputs/Outputs
- Open Collector TTL/CMOS Output
- AC-Coupled Input (External Bias)

QUICK REFERENCE DATA

- Supply Voltage: $-5.2V\pm0.25V$ (ECL), $5.0V\pm0.25V$ (TTL)
- Power Consumption: 260mW
- Temperature Range: -30°C to +70°C

ABSOLUTE MAXIMUM RATINGS

Supply voltage, $ V_{CC} - V_{EE} $	8V
Output current	20mA
Storage temperature range	-65°C to $+150$ °C
Max. junction temperature	+175°C
Open collector voltage (pin 11)	+12V
Max. clock input voltage	2·5V p-p
Max. open collector current	15mA




Fig. 1 Pin connections - top view

ORDERING INFORMATION

SP8647 B DG 5962-90618 (SMD)




Fig. 2 Functional diagram

ELECTRICAL CHARACTERISTICS

Unless otherwise stated, the Electrical Characteristics are guaranteed over specified supply, frequency and temperature range **ECL OPERATION**

Supply voltage, V_{CC} = 0V, V_{EE} = -5.2V \pm 0.25V Temperature, T_{AMB} = -30°C to +70°C

Characteristic	Cumbal	Value		Units	Conditions	Notes
Characteristic	Symbol	Min. Max.	Units			
Maximum frequency (sinewave input)	f _{MAX}	250		MHz	Input = 400-800mV p-p	5
Minimum frequency (sinewave input)	f _{MIN}		50	MHz	Input = 400-800mV p-p	5
Power supply current	I _{EE}		65	mA	$V_{EE} = -5.2V$	5
ECL output high voltage	V _{OH}	-0.85	-0.7	V	V _{EE} = −5·2V (25°C)	
ECL output low voltage	V_{OL}	−1.8	−1.5	V	V _{EE} = −5·2V (25°C)	
Clock and PE input high voltage	V_{INH}	-0.93		V	V _{EE} = −5·2V (25°C)	
Clock and PE input low voltage	V_{INL}		-1.62	V	V _{EE} = −5·2V (25°C)	
Clock to ECL output delay	t _p		6	ns		6
Set-up time	ts	2.5		ns		3, 6
Release time	t _r	3		ns		4, 6

TTL OPERATION

Supply voltage, $V_{CC} = 5V \pm 0.25V$, $V_{EE} = 0V$ Temperature, $T_{AMB} = -30^{\circ}C$ to $+70^{\circ}C$

Characteristic	Cumbal	Value		Units	Conditions	Notes
Characteristic	Symbol	Min.	Max.	Oilles	Conditions	Notes
Maximum frequency (sinewave input)	f _{MAX}	250		MHz	Input = 400-800mV p-p	5
Minimum frequency (sinewave input)	f _{MIN}		50	MHz	Input = 400-800mV p-p	5
Power supply current	I _{EE}		65	mA		5
TTL output low voltage	V _{OL}		0.5	V	$V_{CC} = 5.25V$, sink current = 8mA	5, 7
TTL output high voltage	V _{OH}	3.5		V	$V_{CC} = 5.0V$	5, 7
Clock to TTL output high delay,+ve going	t _{PLH}		15	ns		6
Clock to TTL output low delay, -ve going	t _{PHL}		15	ns		6
Set-up time	ts	2.5		ns		3, 6
Release time	t _r	3		ns		4, 6

- The temperature coefficients of V_{OH} = +1·63mV/°C, V_{OL} = +0·94mV/°C and of V_{IN} = +1·22mV/°C.
 The test configuration for dynamic testing is shown in Fig.6.
 The set-up time t_s is defined as the minimum time that can elapse between L→H transition of control input and the next L→H clock pulse transition to ensure that the ÷10 mode is obtained.
- 4. The release time t_f is defined as the minimum time that can elapse between $H \rightarrow L$ transition of control input and the next $L \rightarrow H$ clock pulse transition to ensure that the ÷11 mode is obtained.
- Tested at 25°C only.
- 6. Guaranteed but not tested.
- 7. The open collector output is not recommended for use at output frequencies above 15MHz. C_{LOAD} ≤ 5pF.





Fig. 3 Typical input characteristic



TRUTH TABLE FOR CONTROL INPUTS

<u>PE1</u>	PE2	Division ratio
L	L	11
Н	L	10
L	Н	10
Н	Н	10

Fig. 4 Timing diagram




Fig. 5 Typical input impedance. Test conditions: Supply Voltage = 5V, Ambient Temperature = 25° C. Frequencies in MHz, impedances normalised to 50Ω .

OPERATING NOTES

- 1. The clock and control inputs are ECLIII compatible. There is an internal pulldown resistor to V_{EE} of $4\cdot 3k\Omega$ on each input and therefore any unused input can be left open circuit. If it is desirable to capacitively couple the signal source to the clock then an external bias is required as shown in Fig. 6. The external bias voltage should be $-1\cdot 3V$ at $25^{\circ}C$.
- 2. The outputs are compatible with ECLII but can be interfaced to ECL10K as shown in Fig.8.
- 3. The circuit will operate down to DC but slew rate must be better than $100V/\mu s$.
- 4. Input impedance is a function of frequency. See Fig. 5.5. The TTL/CMOS output is a free collector, with an output
- is the TECONOS output is a free conector, with an output rise/fall time which is a function of load resistance and load capacitance. The load capacitance should therefore be kept to a minimum and the load resistance should not be too small otherwise V_{OL} will be too great. For example, TTL output current = 8mA, V_{OL} = 0.5V. For CMOS outputs, the value of load resistor should be the maximum consistent with satisfactory rise times.
- 6. All components should be suitable for the frequency in use.




Fig. 6 Test circuit




Fig. 7 Typical application showing TTL interfacing. NB: Voltage at TP1 should be +3.75V at 25° C.





Fig. 8 Interfacing to ECL10K

NOTES

PACKAGE DETAILS

Dimensions are shown thus: mm (in).





HEADQUARTERS OPERATIONS **GEC PLESSEY SEMICONDUCTORS**

Cheney Manor, Swindon, Wiltshire SN2 2QW, United Kingdom. Tel: (0793) 518000

Fax: (0793) 518411

GEC PLESSEY SEMICONDUCTORS

P.O. Box 660017 1500 Green Hills Road. Scotts Valley, CA95067-0017 United States of America. Tel (408) 438 2900 Fax: (408) 438 5576

CUSTOMER SERVICE CENTRES

- FRANCE & BENELUX Les Ulis Cedex Tel: (1) 64 46 23 45 Fax: (1) 64 46 06 07
- GERMANY Munich Tel: (089) 3609 06-0 Fax: (089) 3609 06-55
- ITALY Milan Tel: (02) 66040867 Fax: (02) 66040993
- JAPAN Tokyo Tel: (3) 5276-5501 Fax: (3) 5276-5510
- NORTH AMERICA Scotts Valley, USA Tel: (408) 438 2900 Fax: (408) 438 7023. SOUTH EAST ASIA Singapore Tel: (65) 3827708 Fax: (65) 3828872
- **SWEDEN** Stockholm Tel: 46 8 702 97 70 Fax: 46 8 640 47 36
- **UK, EIRE, DENMARK, FINLAND & NORWAY** Swindon Tel: (0793) 518510 Fax: (0793) 518582

These are supported by Agents and Distributors in major countries world-wide.

© GEC Plessey Semiconductors 1994 Publication No. DS3643 Issue No. 1.2 March 1994

This publication is issued to provide information only which (unless agreed by the Company in writing) may not be used, applied or reproduced for any purpose nor form part of any order or contract nor to be regarded as a representation relating to the products or services concerned. No warranty or guarantee express or implied is made regarding the capability, performance or suitability of any product or service. The Company reserves the right to alter without prior knowledge the specification, design or price of any product or service. Information concerning possible methods of use is provided as a guide only and does not constitute any guarantee that such methods of use will be satisfactory in a specific piece of equipment. It is the user's responsibility to fully determine the performance and suitability of any equipment using such information and to ensure that any publication or data used is up to date and has not been superseded. These products are not suitable for use in any medical products whose failure to perform may result in significant injury or death to the user. All products and materials are sold and services provided subject to the Company's conditions of sale, which are available on request.